

// vom erfinder des porty
// by the creator of the porty

Porty Premium Plus

(Artikelnummer: 4954)

- Gespeicherte Energie: 1200 J
- Blende bei 100 ASA 2 m Abstand: f 64,2 **
- Abbrennzeit t 0,5, 1 EHT 3000: 1/1100sec.-(1200J)
- Abbrennzeit t 0,5, 1 EHT 3000: 1/3000sec.-(300J)
- Blitzfolge in Sekunden (230V) Normalladung, 100 %: 2,7 s
- Blitzfolge in Sekunden (230V) Normalladung, min. Energie: 0,4 s
- Leistungsregelung in 1/10 f: 6 Blendenstufen in 1/10 f Schritten
- Leistungsverteilung: asymmetrisch
- Blitzausgänge/Anzahl: 2
- Gewicht in kg: 8,95
- Maße in cm L x B x H: 21 x 12,4 x 32,1
- Blitz und Einstelllicht über Funk steuerbar

Zubehör:

- Funksteuerung Strobe Wizard Plus (Art-Nr. 3950)



ENGLISH

- Stored energy: 1200 J
- Aperture at 100 ASA 2 m distance: f 64,2 **
- Flash Duration t 0,5, 1 EHT 3000: 1/1100sec.-(1200J):
- Flash Duration t 0,5, 1 EHT 3000: 1/3000sec.-(300J)
- Flash Sequence in sec. (230 V) Normal Recycling, 100 %: 2,7 s
- Flash Sequence in sec. (230 V) Normal Recycling, min. energy: 0,4 s
- Output Adjustment in 1/10 stops: 6 f
- Output Distribution: asymmetrical
- Flash Outlets/Number: 2
- Weight in kg: 8,95
- Dimensions in cm L x W x H: 21 x 12,4 x 32,1
- Radio controlled flash and modeling light

Accessories:

- Strobe Wizard Plus Transmitter (Art-Nr. 3950)

HENSEL
performing light